


# Smart dimmer module

## NS-DMD / 1 CHANNEL / ZIGBEE

Smart lighting control with NETUS App on/off and brightness adjustment.


**ZIGBEE 3.0**

Single-channel dimmer


**SIDE**

Compact profile

**SMART DIMMING**

App on/off and brightness

**LOCAL CONTROL**

External switch input: S1

**COMPACT DESIGN**

39 x 39 x 19 mm

## TECHNICAL SPECIFICATIONS

|                         |                                                                                                             |
|-------------------------|-------------------------------------------------------------------------------------------------------------|
| Model / product type    | NS-DMD / 1-channel Zigbee dimmer module                                                                     |
| Supply                  | 100-240 V AC, 50/60 Hz; neutral required                                                                    |
| Wireless / gateway      | Zigbee 3.0; compatible NETUS gateway required                                                               |
| LED load rating         | 150 W at 230 V AC; 80 W at 120 V AC                                                                         |
| Connections             | L: supply; N: neutral; L1: dimmed output; S1: switch input                                                  |
| Control platform        | NETUS App: on/off and brightness adjustment                                                                 |
| Operating temperature   | -10°C to +40°C                                                                                              |
| Protection / dimensions | IP20 / 39 x 39 x 19 mm (W x H x D)                                                                          |
| Installation            | Compact format for installation behind a wall switch. Mounting bracket shown in the supplier specification. |

## DIMENSIONS



## LIGHTING APPLICATION

Use compatible dimmable LED lamps or drivers. Confirm the dimming method and load compatibility before installation.

App timing, countdown, schedules, grouping and sharing depend on the NETUS App and installed firmware.